

**WARRANTY
REGISTRATION:**
register online today for a chance
to win a FREE Tripp Lite product—
www.tripplite.com/warranty



Owner's Manual

Protect It!™ Surge Suppressors



Important Safety Instructions	1
Installation	2
FCC Part 68 Notice	3
Lifetime Limited Warranty	3
Warranty Registration	4
Ultimate Lifetime Insurance Policy	4
Español	4
Français	7

Important Safety Instructions

SAVE THESE INSTRUCTIONS

CAUTION! DO NOT connect to an ungrounded outlet. DO NOT use with 2-wire extension cords or adapters. This surge suppressor is designed for indoor use only. Install the surge suppressor away from heat-emitting appliances such as radiators or heat registers. Do not install where excessive moisture is present. Do not plug extension cords into it. Never install electrical, telephone, network or coaxial wiring during a lightning storm. Do not drill into any part of the housing or open the housing for any reason. There are no user-serviceable parts inside.



Installation

Mount Your Surge Suppressor (Optional Installation. Available on Select Models Only):

If desired, mount your surge suppressor on a wall or other sturdy, vertical surface. However, you must mount the surge suppressor prior to connecting your equipment. Place a sheet of paper over the surge suppressor's mounting holes and mark their centers with a push pin. Next, place this template over the desired area and mark with the push pins. Install screws (user supplied) into the marks until ¼ in. (0.6 cm) of the screw heads are exposed. Mount the surge suppressor over the screw heads and slide into place.

Connect Your Surge Suppressor to the AC Power Line: Plug the surge suppressor's power cord into a standard, 3-wire grounded 120V AC outlet.

Turn Your Surge Suppressor ON: Press the surge suppressor's power switch to "ON" or "RESET" (depending on model). Select models feature an illuminated switch.

Check Your Surge Suppressor's Diagnostic Indicator Lights (Available on Select Models Only): If your surge suppressor features diagnostic LEDs, check them prior to connecting your equipment. They will indicate various operating conditions when the surge suppressor is plugged into a live 120V AC outlet and the surge suppressor's power switch is on.

"PROTECTED" LED: Indicates the surge suppression components are intact and providing complete protection against surges. If this LED does not illuminate, some of the surge suppression components are not functioning, and the unit should be replaced. Call Tripp Lite Customer Support at (773) 869-1234.

"GROUNDED" LED: Indicates wall outlet is grounded and surge protection can properly function. If this light DOES NOT illuminate and power is present, consult a qualified electrician to examine your outlet's wiring.

"LINE OK" LED (select models): Indicates 120V AC power is present with no wiring faults detected.

Connect Your Equipment to the Surge Suppressor's AC Outlets: Plug your equipment's power cords (including 2-wire devices) into the surge suppressor's AC outlets. Select models feature integrated safety covers which cover the outlets when not in use. Other models feature special widely-spaced outlets to accommodate transformers without covering other outlets. DO NOT plug in extension cords. DO NOT OVERLOAD the surge suppressor's outlets. The surge suppressor can accommodate a total equipment load of up to 15 amps (whether plugged into a single outlet or spread out over multiple outlets). If the load on the surge suppressor exceeds 15 amps, the circuit breaker* will trip and the outlets will stop providing power. If the circuit breaker trips, reduce the load by unplugging some devices. Depress the circuit breaker to reset.

** Circuit breakers are integrated into the power switch on select models and offered as a separate feature on other models.*

Connect Your Equipment to the Surge Suppressor's Phone Jacks (Optional Installation. Available on Select Models Only):

Connect a phone cable from the wall jack directly to the surge suppressor's RJ-style phone jack labeled "IN." Connect a phone cable from the surge suppressor's RJ-style phone jack labeled "OUT" directly to the device to be protected. Select models feature two "OUT" jacks; either one or both of the jacks may be used, but protection is for a device or devices sharing a single line only. All models with phone line surge protection, except the TLP810NET, protect devices on a single line only. TLP810NET models feature a single set of RJ-style phone jacks which protect devices on two lines. The surge suppressor must always be the first item connected in line from the wall jack. The surge suppressor must be plugged into a 3-wire, grounded AC outlet for phone line surge protection to work.

Connect Your Equipment to the Surge Suppressor's Network Jacks* (Optional Installation. Available on Select Models Only): Connect a data cord from the wall jack or cable/DSL modem directly to the surge suppressor's network jack labeled "IN." Connect a data

** 10/100 BaseT/TX, Token Ring. Not compatible with PoE (Power Over Ethernet) applications.*

Installation *(continued)*

cord from the surge suppressor's network jack labeled "OUT" directly to the device to be protected (typically a computer's network interface card). The surge suppressor must always be the first item connected in line from the Ethernet source (typically a wall jack). The surge suppressor must be plugged into a 3-wire grounded AC outlet for network line surge protection to work.

Connect Your Equipment to the Surge Suppressor's Coaxial Jacks (Optional Installation. Available on Select Models Only): Connect a coaxial cable from the wall jack directly to the surge suppressor's "F" style coaxial jack labeled "IN." Connect a coaxial cable from the surge suppressor's "F" style coaxial jack labeled "OUT" directly to the device to be protected. Select models include a second set of coaxial jacks for simultaneous connection and protection of devices on two separate lines (cable, antenna or satellite). The surge suppressor must always be the first item connected in line from the coaxial wall jack. The surge suppressor must be plugged into a 3-wire grounded AC outlet for coaxial line surge protection to work.

FCC Part 68 Notice *(United States Only)*

If your Modem/Fax Protection causes harm to the telephone network, the telephone company may temporarily discontinue your service. If possible, they will notify you in advance. If advance notice isn't practical, you will be notified as soon as possible. You will be advised of your right to file a complaint with the FCC. Your telephone company may make changes in its facilities, equipment, operations or procedures that could affect the proper operation of your equipment. If it does, you will be given advance notice to give you an opportunity to maintain uninterrupted service. If you experience trouble with this equipment's Modem/Fax Protection, please call Tripp Lite Technical Support at (773) 869-1234 for repair/warranty information. The telephone company may ask you to disconnect this equipment from the network until the problem has been corrected or you are sure the equipment is not malfunctioning. There are no repairs that can be made by the customer to the Modem/Fax Protection. This equipment may not be used on coin service provided by the telephone company. Connection to party lines is subject to state tariffs. (Contact your state public utility commission or corporation commission for information.)

Lifetime Limited Warranty

Seller warrants this product, if used in accordance with all applicable instructions, to be free from original defects in material and workmanship for its lifetime. If the product should prove defective in material or workmanship within that period, Seller will repair or replace the product, in its sole discretion. Service under this Warranty can only be obtained by your delivering or shipping the product (with all shipping or delivery charges prepaid) to: Tripp Lite, 1111 W. 35th St., Chicago, IL 60609. Seller will pay return shipping charges.

The warranties of all TRIPP LITE surge suppressors are null and void if they have been connected to the output of any UPS system. The warranties of all TRIPP LITE UPS Systems are null and void if a surge suppressor has been connected to its output receptacles.

THIS WARRANTY DOES NOT APPLY TO NORMAL WEAR OR TO DAMAGE RESULTING FROM ACCIDENT, MISUSE, ABUSE OR NEGLIGENCE. SELLER MAKES NO EXPRESS WARRANTIES OTHER THAN THE WARRANTY EXPRESSLY SET FORTH HEREIN. EXCEPT TO THE EXTENT PROHIBITED BY APPLICABLE LAW, ALL IMPLIED WARRANTIES, INCLUDING ALL WARRANTIES OF MERCHANTABILITY OR FITNESS, ARE LIMITED IN DURATION TO THE WARRANTY PERIOD SET FORTH ABOVE; AND THIS WARRANTY EXPRESSLY EXCLUDES ALL INCIDENTAL AND CONSEQUENTIAL DAMAGES. (Some states do not allow limitations on how long an implied warranty lasts, and some states do not allow the exclusion or limitation of incidental or consequential damages, so the above limitations or exclusions may not apply to you. This Warranty gives you specific legal rights, and you may have other rights which vary from jurisdiction to jurisdiction.)

WARNING: The individual user should take care to determine prior to use whether this device is suitable, adequate or safe for the use intended. Since individual applications are subject to great variation, the manufacturer makes no representation or warranty as to the suitability or fitness of these devices for any specific application.

The policy of Tripp Lite is one of continuous improvement. Specifications are subject to change without notice.

Regulatory Compliance Identification Numbers

For the purpose of regulatory compliance certifications and identification, your Tripp Lite product has been assigned a unique series number. The series number can be found on the product nameplate label, along with all required approval markings and information. When requesting compliance information for this product, always refer to the series number. The series number should not be confused with the marking name or model number of the product.

Warranty Registration

Visit www.tripplite.com/warranty today to register the warranty for your new Tripp Lite product. You'll be automatically entered into a drawing for a chance to win a FREE Tripp Lite product!*

* No purchase necessary. Void where prohibited. Some restrictions apply. See website for details.

Ultimate Lifetime Insurance Policy

(This is a limited warranty valid in the U.S. and Canada only.)

Tripp Lite warrants, for the lifetime of the product, (at Tripp Lite's option) to repair or replace (on a pro rata basis) directly connected equipment that is damaged due to power transients while properly connected to Tripp Lite products offering the Ultimate Lifetime Insurance Policy. Power transients include spikes and surges on the AC power, data or telephone lines that the Tripp Lite products have been designed to protect against (as recognized by industry standards). The following four paragraphs are conditions that must be complied with before the warranty becomes valid; failure to comply with these requirements will void the warranty.

AC Power Line Transients: To claim damages, the Tripp Lite product must be plugged into a properly wired and grounded outlet. No extension cords or other electrical connections may be used. The installation must comply with all applicable electrical and safety codes set forth by the National Electrical Code (NEC). Except as provided above, this warranty does not cover any damage to properly connected electronic equipment resulting from a cause other than an "AC power transient". If user meets all of the above requirements, Tripp Lite will repair or replace (at Tripp Lite's option) equipment up to the specified value (See Ultimate Lifetime Insurance Policy Limits). No coverage is allowed for damage entering from telephone or data lines, unless they are separately protected, as described below.

Telephone and Data Line Transients: Tripp Lite will repair or replace directly connected equipment that is damaged by transients on telephone and/or data lines only when all such paths are protected by a Tripp Lite protection product(s) and the AC power (utility) line is simultaneously protected by a Tripp Lite power protection device (UPS, surge suppressor or line conditioner) with Ultimate Lifetime Insurance coverage. Additional telephone and/or data line connected devices downstream must have their own telephone and/or data line protectors.

Reimbursement dollar limits will be equal to that of the Tripp Lite power protection protector. Coverage is excluded where a suitable environment for the protection device is not provided, including, but not limited to, lack of a proper safety ground. Telephone service equipment must also include a properly installed and operating "primary protection" device at the telephone service entrance (such devices are normally added during telephone line installation).

All above warranties are null and void if the Tripp Lite product has been improperly installed, tampered with or altered in any way, or if the connected equipment was not used under normal operating conditions or in accordance with any labels or instructions. All claims under this warranty must be submitted in writing to Tripp Lite within 30 days of the occurrence or the claim will not be considered. This warranty does not include damage resulting from accident or misuse, and applies to the domestic (USA & Canada) use of these products only. Tripp Lite reserves the right to determine whether the damage to the connected equipment is due to malfunction of the Tripp Lite product by requesting the equipment in question be sent to Tripp Lite for examination. This policy is above and beyond, only to the extent needed, of that provided by any coverage of connected equipment provided by other sources, including, but not limited to, any manufacturer's warranty and/or any extended warranties.

EXCEPT AS PROVIDED ABOVE, TRIPP LITE MAKES NO WARRANTIES, EXPRESS OR IMPLIED, INCLUDING WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. Some states do not permit limitation or exclusion of implied warranties; therefore, the aforesaid limitation(s) or exclusion(s) may not apply to purchaser. EXCEPT AS PROVIDED ABOVE, IN NO EVENT WILL TRIPP LITE BE LIABLE FOR DIRECT, INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OF THIS PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE. Specifically, Tripp Lite is not liable for any costs, such as lost profits or revenue, loss of equipment, loss of use of equipment, loss of software, loss of data, costs of substitutes, claims by third parties or otherwise. Coverage also does not apply to connected medical and industrial equipment.

To receive service under this warranty, you must be the original purchaser/user of the product in question. You must obtain a Returned Material Authorization (RMA) number from Tripp Lite. Products must be returned to Tripp Lite with transportation charges prepaid and must be accompanied by a brief description of the problem encountered and proof of date and place of purchase.



Supresores de
sobretensiones
Protect It!™



Manual del
propietario

INSTRUCCIONES DE SEGURIDAD IMPORTANTES



GUARDE ESTAS INSTRUCCIONES

¡PRECAUCIÓN! NO lo conecte a una salida que no esté conectada a tierra. NO lo use con cordones de extensión de 2 conductores ni con adaptadores. Este supresor de sobretensiones está diseñado sólo para usarse bajo techo. Instale el supresor de sobretensiones lejos de dispositivos emisores de calor como radiadores o registros de calor. No lo instale donde haya excesiva humedad. No conecte cordones de extensión. Nunca instale ningún cableado eléctrico, telefónico, de red o coaxial durante una tormenta eléctrica. No taladre en ninguna parte de la cubierta ni la abra por ningún motivo. No hay partes que requieran mantenimiento por parte del usuario en su interior.

Instalación

Monte su supresor de sobretensiones (Instalación opcional. Disponible sólo en modelos exclusivos): Si lo desea, monte su supresor de sobretensiones en una pared o en otra superficie sólida y vertical. Sin embargo, debe montar el supresor antes de conectar su equipo. Coloque una hoja de papel sobre los agujeros de montaje del supresor y marque sus centros con un push pin. Luego, coloque esta plantilla sobre el área deseada y marque con un push pin. Instale los tornillos (suministrados por el usuario) en las marcas hasta que ¼" (0.6 cm) de las cabezas de los tornillos estén visibles. Monte el supresor de sobretensiones sobre las cabezas de tornillo y deslícelo hasta que esté en posición.

Conecte su supresor de sobretensiones en la línea de corriente alterna: Conecte el cordón de alimentación del supresor en una salida estándar bipolar con toma de tierra de 120 V CA.

Encienda su supresor de sobretensiones: Presione el interruptor de alimentación en la posición "ON" o "RESET" (dependiendo del modelo) Los modelos exclusivos tienen un interruptor con iluminación.

Verifique las luces de diagnóstico de su supresor de sobretensiones (Disponible sólo en modelos exclusivos): Si su supresor tiene LEDs de diagnóstico, verifíquelos antes de conectar su equipo. Ellas le indicarán varias condiciones de operación cuando el supresor de sobretensiones esté conectado en una salida con energía de 120 V CA y cuando el interruptor de alimentación del supresor esté encendido.

LED "PROTECTED" (PROTEGIDO): Indica que los componentes de supresión de sobretensiones están intactos y proporcionando protección completa contra sobretensiones. Si este LED no se ilumina, algunos de los componentes del sistema de supresión de sobretensiones no están funcionando y la unidad debe ser reemplazada. Llame al Servicio al cliente de Tripp Lite al (773) 869-1234.

LED "GROUNDED" (TIERRA): Indica que la toma de corriente de pared está a tierra y que la protección contra sobretensiones funciona correctamente. Si hay energía eléctrica pero esta luz NO se enciende, pida a un electricista calificado que revise el cableado de su tomacorriente.

LED "LINE OK" (LÍNEA ESTABLE) (en modelos selectos): Indica la presencia de un voltaje de 120V CA sin ninguna falla detectada en la instalación eléctrica.

Conecte su equipo en las salidas de CA del supresor: Conecte los cordones de alimentación de su equipo (incluyendo dispositivos bipolares) en las salidas de CA del supresor. Los modelos exclusivos tienen cubiertas de seguridad integradas que cubren las salidas cuando no están en uso. Otros modelos tienen salidas especiales ampliamente espaciadas para acomodar transformadores sin obstruir otras salidas. NO conecte cordones de extensión. NO SOBRECARGUE las salidas del supresor de sobretensiones. El supresor de sobretensiones puede acomodar una carga total de equipos de hasta 15 amperios (ya sea que estén conectados en una sola o en varias salidas) Si la carga en el supresor de sobretensiones excede 15 amperios, el interruptor automático* disparará y las salidas dejarán de proporcionar alimentación. Si el interruptor automático dispara, reduzca la carga desconectando algunos dispositivos. Presione el interruptor automático para restablecerlo.

** Los interruptores automáticos están integrados en el interruptor de alimentación en los modelos exclusivos y se ofrecen como una función separada en otros modelos.*

Conecte su equipo a los conectores telefónicos del supresor de sobretensiones (Instalación opcional. Disponible sólo en modelos exclusivos): Conecte un cable de teléfono desde el conector de pared directamente hasta el conector de teléfono RJ etiquetado "IN" en el supresor. Conecte un cable telefónico desde el conector de teléfono RJ etiquetado "OUT" en el supresor directamente hasta el dispositivo que debe protegerse. Los modelos exclusivos presentan dos conectores "OUT"; pueden usarse uno sólo o ambos, pero la protección es para un dispositivo o dispositivos que compartan una sola línea. Todos los modelos con protección contra sobretensiones en líneas de teléfono, excepto el TLP810NET, protegen dispositivos en una sola línea solamente. Los modelos TLP810NET tienen un juego simple de conectores de teléfono RJ que protegen dispositivos en dos líneas. El supresor de sobretensiones siempre debe ser el primer elemento conectado en línea desde el conector de pared. El supresor debe estar conectado en una toma de corriente alterna bipolar con toma de tierra para que funcione la protección contra sobretensiones en la línea telefónica.

Conecte su equipo a los conectores de red del supresor de sobretensiones (Instalación opcional. Disponible sólo en modelos exclusivos): Conecte un cable de datos desde el conector de pared o cable/módem DSL directamente a un conector de red etiquetado "IN" en el supresor de sobretensiones. Conecte un cable de datos desde el conector de red etiquetado "OUT" en el supresor de sobretensiones directamente al dispositivo que debe protegerse (usualmente una tarjeta de interfaz de red de una computadora) El supresor de sobretensiones siempre debe ser el primer elemento conectado en línea desde la fuente Ethernet (usualmente un conector de pared) El supresor debe estar conectado en una toma de corriente alterna bipolar con toma de tierra para que funcione la protección contra sobretensiones en la línea de red.

** 10/100 Base/TX, Token Ring. No compatible con aplicaciones PoE (Energía sobre Ethernet).*

Instalación (continuación)

Conecte su equipo a los conectores coaxiales del supresor de sobretensiones (Instalación opcional. Disponible sólo en modelos exclusivos): Conecte un cable coaxial desde el conector de pared directamente hasta el conector coaxial tipo F etiquetado "IN" en el supresor. Conecte un cable coaxial desde el conector coaxial tipo F etiquetado "OUT" en el supresor directamente al dispositivo que debe protegerse. Los modelos exclusivos incluyen un segundo juego de conectores coaxiales para conexión y protección simultánea de dispositivos en dos líneas separadas (cable, antena o satélite) El supresor de sobretensiones siempre debe ser el primer elemento conectado en línea desde el conector coaxial de pared. El supresor debe estar conectado en una toma de corriente alterna bipolar con toma de tierra para que funcione la protección contra sobretensiones en la línea coaxial.

Garantía Vitalicia Limitada

El Vendedor garantiza que este producto, si se utiliza conforme a todas las instrucciones pertinentes, estará exento de defectos originales en el material y la fabricación durante toda su vida (en México: 25 años). Si el producto presenta algún defecto de material o fabricación dentro de ese plazo, el Vendedor lo reparará o sustituirá a su criterio exclusivo. El servicio bajo esta Garantía se ofrecerá sólo si usted entrega o envía el producto (habiendo pagado todos los gastos de flete o transporte) a: Tripp Lite, 1111 W. 35th St., Chicago, IL 60609, EE.UU. El Vendedor correrá con los gastos de envío del producto al cliente. Las garantías de todos los supresores de sobretensiones de Tripp Lite serán anuladas si estos supresores han sido conectados a los receptáculos de salida de cualquier sistema UPS. Las garantías de todos los Sistemas UPS de Tripp Lite serán anuladas si se ha conectado algún supresor de sobretensiones a los receptáculos de salida del sistema UPS en cuestión. ESTA GARANTÍA NO APLICA EN CASO DE DESGASTE NORMAL O DAÑOS QUE SE ORIGINEN DE ACCIDENTES, MALTRATO, ABUSO O NEGLIGENCIA. EL VENDEDOR NO OFRECE NINGUNA OTRA GARANTÍA EXPRESA APARTE DE LA QUE SE ENUNCIAN EXPLÍCITAMENTE EN ESTE DOCUMENTO. SALVO HASTA DONDE LO PROHIBA LA LEY VIGENTE, LA DURACIÓN DE TODAS LAS GARANTÍAS IMPLÍCITAS, INCLUIDAS LAS DE COMERCIALIZACIÓN O IDONEIDAD, ESTÁ LIMITADA AL PLAZO ENUNCIADO ANTERIORMENTE. ESTA GARANTÍA EXCLUYE EXPRESAMENTE TODOS LOS PERJUICIOS FORTUITOS Y RESULTANTES. (Ya que algunas jurisdicciones no permiten imponer limitaciones a la duración de una garantía implícita o prohíben la exclusión o limitación de daños fortuitos o resultantes, puede que las limitaciones o exclusiones antedichas no rijan en todos los casos. Esta Garantía le otorga derechos legales específicos, y es posible que usted tenga otros derechos que dependen de la jurisdicción.)

ADVERTENCIA: Antes de usar este dispositivo el usuario es responsable de determinar si es idóneo, adecuado o inocuo para el uso previsto. Ya que cada aplicación está sujeta a enormes variaciones, el fabricante no ofrece ninguna representación o garantía respecto a la idoneidad o adaptabilidad de estos dispositivos para determinada aplicación. La política de Tripp Lite es el mejoramiento continuo. Las especificaciones están sujetas a cambio sin previo aviso.

Cumplimiento de las normas de los números de identificación

Para fines de identificación y certificación del cumplimiento de las normas, su producto Tripp Lite tiene asignado un número de serie único. Puede encontrar el número de serie en la etiqueta de la placa de identificación del producto, junto con los símbolos de aprobación e información requeridos. Al solicitar información sobre el cumplimiento de las normas para este producto, siempre mencione el número de serie. El número de serie no debe ser confundido con el nombre de identificación ni con el número de modelo del producto.

LEA SU INSTRUCTIVO CONSULTE SUS CONDICIONES DE GARANTÍA POR PRODUCTO PÓLIZA DE GARANTÍA

Este equipo marca Tripp Lite, modelo _____ está garantizado por TRIPP LITE, que tiene su domicilio en la calle de Sierra Candela No.111-107, Col Lomas de Chapultepec, CP 11000, México, DF, y puede hacer efectiva su garantía así como obtener partes, componentes, consumibles y accesorios en el Centro de Servicio Q PLUS ubicado en Av Coyocacan 931, Col. Del Valle, C.P. 03120 México. D.F., tel. 50 00 27 00 contra cualquier defecto de fabricación y funcionamiento, imperfecciones de materiales, piezas, componentes y mano de obra al consumidor acorde a la siguiente tabla:

Producto	Modelo	Vigencia
Sistema de Energía Ininterrumpible (UPS)	Familia: BC, OMNI, SMART, SMARTONLINE MONOFASICOS	2 Años
Sistema de Energía Ininterrumpible (UPS)	Familia: SMARTONLINE 3PH	1 Año
Regulador y Acondicionador de Tensión	Familia: LS, LC	2 Años
Inversores	Familia: APS, PV	2 Años
Multiplexor y Conmutador	Familia: KVM	5 Años
Conmutador	Modelo: B020-016	6 Meses
Supresor de Picos de Tensión	Familia: PROTECT IT, ISOBAR	25 Años

CONDICIONES

- Para hacer válida su garantía no podrán exigirse mayores requisitos que la presentación de esta póliza debidamente llenada y sellada por el establecimiento que lo vendió junto con el producto en el lugar donde fue adquirido.
- TRIPP LITE, se compromete a reparar, y en caso de que a su juicio no sea posible la reparación, a cambiar el equipo, así como las piezas y componentes defectuosos del mismo sin cargo alguno para el propietario durante el periodo de garantía, así como los gastos de transportación razonablemente erogados del producto que deriven de su cumplimiento, dentro de su red de servicio.
- El tiempo de reparación en ningún caso será mayor de 30 días contados a partir de la fecha de recepción del producto en el Centro Autorizado de Servicio, en donde también podrán adquirir refacciones y partes.
- En caso de que la presente póliza de garantía se extravíara, el consumidor puede recurrir a su proveedor para que expida un duplicado de la póliza de garantía, previa presentación de la nota de compra o factura correspondiente.

EXCLUSIONES

Esta garantía no es válida en los siguientes casos:

- Cuando el producto se hubiese utilizado en condiciones distintas a las normales.
- Cuando el producto no hubiese sido operado de acuerdo con el instructivo de uso que se le acompaña.
- Cuando el producto hubiese sido alterado o reparado por personas no autorizadas por el fabricante nacional, importador o comercializador responsable respectivo.

Este equipo fue vendido por: _____ con domicilio en _____
el día ____ de _____ de _____, fecha a partir de la que inicia la presente garantía.



1111 W. 35th Street, Chicago, IL 60609 USA
773.869.1234 (USA) • 773.869.1212 (International)
www.triplite.com