



120V 750VA 450W Home Theater Line-Interactive UPS with USB, 12 Outlets and Tel/DSL/Coax Protection

MODEL NUMBER: HT850UPS





Description

Tripp Lite's HT850UPS line-interactive UPS offers complete protection for PCs, workstations and other sensitive electronics in an ultra-compact, mountable housing. Internal UPS circuits support individual VCR/DVR components as long as 3 hours during power failures. Prevents data loss and system downtime by providing battery-supported AC output during blackouts and automatic voltage regulation (AVR) during brownouts and overvoltages. Includes 12 output receptacles, 4 of which are widely spaced to accommodate large transformer blocks without obscuring adjacent outlets. 6 outlets offer full battery support and surge suppression, protecting computers, monitors and other vital system components from power loss. 6 additional outlets with surge suppression only are ideal for printers and other peripherals not requiring battery support. Single-line telephone suppression jacks protect modems, fax machines, cordless phones or other equipment with a DSL or standard dialup RJ-11 phone line connection. Set of gold coaxial line surge suppression jacks protect CATV, satellite or broadcast antenna connections. USB communications interface with PowerAlert monitoring software (free via web download) and cabling enables a safe, unattended system shutdown. HID-compliant USB port enables integration with built-in power management and auto-shutdown features of Windows and Mac OS X. Audible alarm and front panel LEDs offer status information regarding line and battery power operation, 450W power-handling ability supports entry-level PCs for up to 35 min. during power failures. \$100,000 Ultimate Lifetime Insurance (U.S., Canada, and Puerto Rico only).

Features

- HT850UPS line-interactive UPS offers protection from blackouts, brownouts and surges on AC, tel/DSL and coaxial line connections
- Built-in automatic voltage regulation (AVR) boosts brownouts as low as 83V and reduces overvoltages
 up to 147V back to usable 120V nominal levels
- 12 AC outlets, 4 of which are widely spaced to accommodate large transformer blocks without obscuring adjacent outlets
- 6 UPS battery-supported outlets protect computers, monitors and vital system peripherals; 6 additional surge suppression-only outlets protect system accessories not requiring battery support

Highlights

- 750VA ultra-compact 120V line interactive UPS for home theater
- Corrects brownouts and overvoltages from 83V to 147V
- 6 UPS battery supported outlets, 6 surge-only outlets
- USB port, TEL/DSL/Coax protection, Wall mountable, 98% efficient
- NEMA 5-15P input plug and 12 NEMA 5-15R outlets

Package Includes

- HT850UPS UPS System
- USB cable
- Phone cable
- · Gold coax cable
- Instruction manual





- Provides battery-derived AC output during blackouts, voltage boost during brownouts and voltage reduction during overvoltages
- 750VA/450W power-handling ability supports a variety of home theater equipment, workstations and other sensitive electronics
- Supports individual VCR/DVR components as long as 3 hours during power failures
- Built-in single-line tel/DSL surge suppression protects modems, fax machines or cordless phones. Builtin coaxial line surge suppression protects CATV, satellite or broadcast antenna connections
- Built-in USB port enables data-saving unattended shutdown when used with Tripp Lite's PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- HID-compliant USB port enables integration with built-in power management and auto-shutdown features of Windows and Mac OS X
- Supports Tripp Lite's Watchdog system service to restore operation to locked equipment through soft reboot of application/OS or hard power off/on reboot of connected equipment; ideal for unattended kiosk applications
- Hot-swappable user battery replacement supported via battery access door
- Optional PDUB15 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment
- Space-saving, ultra-compact housing fits almost anywhere
- Keyhole mounting flanges enable secure wallmount installation

Specifications

OVERVIEW		
UPC Code	037332127433	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	12A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P; Right-Angled	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
OUTPUT		
Output Capacity (VA)	750	
Output Capacity (Watts)	450	
Nominal Voltage Details	115v nominal output in battery mode	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Line Mode)	+8%, -21%	
Output Voltage Regulation (Battery Mode)	+/- 5%	





UPS Output Receptacides (Surge spersoid On 10%) but UPS outlets, 6 surge only outlets Hot-Swap PDU options PDUB15 (2U / 8 6-15R outlets) Output AC Waveform (AC Mode) 5 ne wave Output AC Waveform (Battery) PWMI sine wave Nominal Output Voltage(s) 110V; 116V; 120V Output Receptacides (12) 6-15R Individually Controllable Load Banks No BATTERY Runtime Full Load (min.) 4 min. (450w) Runtime Full Load (min.) 4 min. (250w) Runtime Full Load (min.) 10 min. (250w) Expandable Runtime No DC System Voltage (VDC) 12 Eathery Access Battery access door Internal UPS Replacement Battery Selbage-acidass-*productLink* heefs-*/Pripplits_eaton.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Cartridge-Tripp-Lite-AP			
Output AC Waveform (AC Mode) Output AC Waveform (Battery Nominal Output Voltage(e) Supported Supported Supported Voltage(e) Supported	UPS Output Receptacles (Surge Suppression Only)	6 UPS outlets, 6 surge-only outlets	
Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(e) 110V; 115V; 120V Output Receptacles (12) 5-15R Individually Controllable Load Banks No BATTERY BATTERY Burnime Half Load (min.) 4 min. (450w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Access Battery access door Internal LPS Replacement Battery Cartridge Battery access door Internal LPS Replacement Description Hor-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Vervoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & COMBANISMORY Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overfoad status LED indicators 2 LEDs indicate power status and overfoad/check battery statu	Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	
Mode) Nominal Output Voltage(s) 110V; 115V; 120V	Output AC Waveform (AC Mode)	Sine wave	
Supported (12) 5-15R Individually Controllable Load Banks No BATTERY Runtine Full Load (min.) 4 min. (450w) Runtime Half Load (min.) 10 min. (225w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Access Battery access door Internal UPS Replacement Battery 8 behav-a classe-"productLint" href"/riripplite auton-cont/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Behin-Best-Powerware-Liebert-other-UPS-RBCS1*-RBCS1	Output AC Waveform (Battery Mode)	PWM sine wave	
Individually Controllable Load Banks BATTERY Runtime Full Load (min.)	Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Runtime Full Load (min.) 4 min. (450w) Runtime Full Load (min.) 10 min. (225w) Expandable Runtime No C System Voltage (VDC) 12 Battery Access Battery access door Internal UPS Replacement Battery & Sattery Access Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Pesponse Instantaneous Inter EL/DSL (1 in / 2 out); Coax jacks (1 set) PHYSICAL PHYSICAL	Output Receptacles	(12) 5-15R	
Runtime Full Load (min.) 4 min. (450w) Runtime Half Load (min.) 10 min. (225w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Access Battery access door Internal LIPS Replacement Battery Belien-Best-Provenware-Liebert-other-UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belien-Best-Powerware-Liebert-other-UPS-RBC51*/sPBC51*/a>&mbsp ac class="productLink" href="///ripplite action.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belien-Best-Powerware-Liebert-other-UPS-RBC51*/sPBC51*/a>&mbsp Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTOLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Joule Rating 400 UPS Control of the TeL/DSL (1 in / 2 out); Coax jacks (1 set) PHYSICAL	Individually Controllable Load Banks	No	
Runtime Half Load (min.) 10 min. (225w) Expandable Runtime No DC System Voltage (VDC) 12 Battery Access Battery access door Internal UPS Replacement Battery & hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Joule Rating Instantaneous EMI / RFI AC Noise Suppression Yes EMI / RFI AC Noise Suppression Yes PHYSICAL	BATTERY		
Expandable Runtime No DC System Voltage (VDC) 12 Battery Access Battery access door Internal UPS Replacement Battery Cartridge* Battery Access Battery access door Internal UPS Replacement Battery Cartridge* Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload/sheck battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes PHYSICAL	Runtime Full Load (min.)	4 min. (450w)	
Battery Access Battery Access Battery access door Internal UPS Replacement Battery Cartridge Replacement Battery Cartridge Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes PHYSICAL	Runtime Half Load (min.)	10 min. (225w)	
Battery Access Battery access door Internal UPS Replacement Battery Cartridge Shbsp. RBC51" /RBC51" <a <a="" href="//tripplite.eaton.com/UPS-Replacement-Battery-Cartridge-Tripp-Lite-APC-Belkin-Best-Powerware-Liebert-other-UPS~RBC51" productlink"="" rbc51"<a="">RBC51			
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147 Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Overvoltage Correction Input voltages between 129 and 147 are reduced by 12% Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes PHYSICAL	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 83 and 104 are boosted by 14% USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) PHYSICAL	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 83 to 147	
USER INTERFACE, ALERTS & CONTROLS Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes	Overvoltage Correction	Input voltages between 129 and 147 are reduced by 12%	
Switches Combination switch controls on/off power status and self-test operation Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes	Undervoltage Correction	Input voltages between 83 and 104 are boosted by 14%	
Audible Alarm Audible alarm indicates power-failure and overload status LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes	USER INTERFACE, ALERTS & CONTROLS		
LED Indicators 2 LEDs indicate power status and overload/check battery status SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) PHYSICAL	Switches	Combination switch controls on/off power status and self-test operation	
SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating 400 UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes	Audible Alarm	Audible alarm indicates power-failure and overload status	
UPS AC Suppression Joule Rating UPS AC Suppression Response Instantaneous UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) PHYSICAL	LED Indicators	2 LEDs indicate power status and overload/check battery status	
UPS AC Suppression Response UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes PHYSICAL	SURGE / NOISE SUPPRESSION		
UPS Dataline Suppression 1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set) EMI / RFI AC Noise Suppression Yes PHYSICAL	UPS AC Suppression Joule Rating	400	
EMI / RFI AC Noise Suppression Yes PHYSICAL		Instantaneous	
PHYSICAL	UPS Dataline Suppression	1 line TEL/DSL (1 in / 2 out); Coax jacks (1 set)	
	EMI / RFI AC Noise Suppression	Yes	
	PHYSICAL		
Primary Form Factor Desktop	Primary Form Factor	Desktop	





Installation Form Factors Supported with Included Accessories	Tower; Ultra-compact desktop; Wallmount	
Primary UPS Depth (mm)	178	
Primary UPS Height (mm)	102	
Primary UPS Width (mm)	305	
Shipping Dimensions (hwd / in.)	5.50 x 14.50 x 9.75	
Shipping Dimensions (hwd / cm)	13.97 x 36.83 x 24.76	
Shipping Weight (lbs.)	16.40	
Shipping Weight (kg)	7.44	
UPS Housing Material	ABS	
UPS Power Module Dimensions (hwd, cm)	10.16 x 30.48 x 17.78	
UPS Power Module Dimensions (hwd, in.)	4 x 12 x 7	
UPS Power Module Weight (kg)	6.89	
UPS Power Module Weight (lbs.)	15.2	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	27	
AC Mode Efficiency Rating (100% Load)	98%	
COMMUNICATIONS		
PowerAlert Software	For local monitoring via the UPS's built-in USB port, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	USB interface cable included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	
Network UPS Tools (NUT) Compatibility	NUT compatible. See the full list of Tripp Lite NUT compatible UPS systems at https://www.networkupstools.org/stable-hcl.html?manufacturer=Tripp Lite	
Communications Interface	USB (HID enabled)	
LINE / BATTERY TRANSFER		
Transfer Time	2 to 4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	83	
High Voltage Transfer to Battery Power (Setpoint)	147	
FEATURES & SPECIFICATIONS		





Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
APPLICATIONS		
UPS Applications	Audio/Video	
WARRANTY & SUPPORT		
Product Warranty Period (Worldwide)	2-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$100,000 Ultimate Lifetime Insurance	

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved.

Eaton is a registered trademark. All other trademarks are the property of their respective owners.