



# OmniSmart 120V 1000VA 700W Line-Interactive UPS, Tower, Built-In Isolation Transformer, USB port

# MODEL NUMBER: OMNI1000ISO





### Description

OMNI1000ISO offers complete UPS protection with built-in line-interactive voltage regulation, intelligent monitoring and unattended shutdown capability. Built-in isolation transformer with Faraday shield offers full isolation and complete common mode noise rejection. 1000VA power-handling capacity supports point-of-sale applications, computers, internetworking equipment and home theater systems during commercial power failures. Line-interactive voltage regulation corrects brownouts as low as 81V and overvoltages as high as 143V back to normal 120V levels, reserving battery power for use during complete power failures. USB communications port works with PowerAlert® software and cabling to provide automatic unattended shutdown of connected network and PC applications.

#### **Features**

- 1000VA line-interactive UPS with Faraday-shielded, low-impedance isolation transformer delivers full isolation from potential damage and performance problems
- Provides immunity from EMI/RFI line noise in both normal and common modes. Delivers clean signalreference ground, reducing data errors and audio/video distortion
- Automatic voltage regulation (AVR) automatically corrects incoming voltage to keep equipment working through low voltage (brownouts) as low as 81V and overvoltages as high as 143V without consuming battery power
- Supports loads up to 1000VA/700W
- Half-load runtime of 24 min. (500VA/350W); full load runtime of 8 min. (1000VA/700W)
- 5 diagnostic LEDs indicate AC present, on battery, voltage correction status, overload and battery low/replace
- · Electrostatic discharge (ESD) resistance reduces potential static damage to connected electronics
- USB port enables data-saving unattended shutdown when used with PowerAlert software, available via FREE download from tripplite.eaton.com/products/power-alert
- Built-in surge suppression (backed by \$200,000 Ultimate Lifetime Insurance U.S., Canada, and Puerto Rico only) safeguards connected equipment against damage
- SURGE VOLTAGE WITHSTAND CAPABILITY: ANSI/IEEE C62.41 Catagories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave
- SURGE VOLTAGE ATTENUATION: N-G 2000:1, L-G 240:1, L-N 100:1
- INSERTION LOSS: 65 db N-G from 10Khz to 100Khz, 45 to 60 db L-G from 10Khz to 100Khz, 18 to 54 db L-N from 50Khz to 500 Khz

## **Highlights**

- 1000VA / 1kVA tower 120V line interactive UPS with isolation transformer
- Corrects brownouts and overvoltages from 81V to 143V
- USB port, Normal & common mode EMI/RFI line noise immunity
- NEMA 5-15P input plug and 6 5-15R outlets

#### **Package Includes**

- OMNI1000ISO UPS System
- USB cable
- Instruction manual



- 6 UPS-supported AC outlets; 6-ft. cord
- Optional PDUB15 bypass PDU enables hot-swappable UPS replacement with no disruption to connected equipment

# **Specifications**

OVERVIEW		
UPC Code	037332126931	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	7.6A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
OUTPUT		
Output Capacity (VA)	1000	
Output Capacity (kVA)	1	
Output Capacity (Watts)	700	
Output Capacity (kW)	0.7	
Output Capacity Details	5.8A @ 120V. 125% @ 10 minutes 110% +/- 10% @ 5 seconds	
Power Factor	0.7	
Nominal Voltage Details	120V in line mode and 115V battery	
Frequency Compatibility	60 Hz	
Frequency Compatibility Details	Output is regulated to +/-0.05Hz when input frequency exceeds +/-5Hz of nominal.	
Output Voltage Regulation (Line Mode)	-18%, +8%	
Output Voltage Regulation (Battery Mode)	+/- 5%	
Hot-Swap PDU options	PDUB15 (2U / 8 5-15R outlets)	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
Nominal Output Voltage(s) Supported	110V; 115V; 120V	
Output Receptacles	(6) 5-15R	





Individually Controllable Load Banks	No	
BATTERY		
Battery Type	Valve Regulated Lead Acid (VRLA)	
Runtime Full Load (min.)	8 min. (700W)	
Runtime Half Load (min.)	24 min. (350W)	
Expandable Runtime	No	
DC System Voltage (VDC)	36	
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%	
Battery Access	Battery access door	
Internal UPS Replacement Battery Cartridge	<a class="productLink" href="//tripplite.eaton.com/UPS-Replacement-Battery-Cartridge-Kit-select-Tripp-Lite-Best-Powerware-Liebert-other-UPS~RBC53">RBC53</a>	
Battery Replacement Description	Hot-swappable, user replaceable batteries	
VOLTAGE REGULATION		
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 85 to 143	
Overvoltage Correction	Input voltages between 128 and 143V are reduced by 9%	
Undervoltage Correction	Input voltages between 96 and 107V are boosted by 10%	
Severe Undervoltage Correction	Input voltages between 85 and 95V are boosted by 20%	
USER INTERFACE, ALERTS & CON	ITROLS	
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
Alarm Cancel Operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low- battery status	
Audible Alarm	Audible alarm indicates power-failure and low-battery conditions	
LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	
ISOLATION		
Output Isolation Transformer	Professional grade load isolation transformer	
Surge Voltage Withstand Capability	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave	
· · · · · · · · · · · · · · · · · · ·		
Surge Voltage Withstand Capability	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave	
Surge Voltage Withstand Capability Surge Voltage Attenuation	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave	
Surge Voltage Withstand Capability Surge Voltage Attenuation SURGE / NOISE SUPPRESSION	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave N-G 2000:1, L-G 240:1, L-N 100:1	
Surge Voltage Withstand Capability Surge Voltage Attenuation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave         N-G 2000:1, L-G 240:1, L-N 100:1         510	
Surge Voltage Withstand Capability Surge Voltage Attenuation SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response Time	ANSI/IEEE C62.41 Categories A & B 6KV/200/500 amp 100Khz Ringwave and category B BiWave N-G 2000:1, L-G 240:1, L-N 100:1 510 Instantaneous	





Cooling Method	Fan
Installation Form Factors Supported with Included Accessories	Tower
Installation Form Factors Supported with Optional Accessories	Wallmount ( <a class="productLink" href="//tripplite.eaton.com/Wall-Mount-Bracket-Installation-Accessories-&lt;br&gt;for-UPS-Systems~UPSWM">UPSWM</a> - tower mounting kit)
Primary UPS Depth (mm)	234
Primary UPS Height (mm)	325
Primary UPS Width (mm)	191
Shipping Dimensions (hwd / in.)	16.90 x 13.50 x 11.30
Shipping Dimensions (hwd / cm)	42.93 x 34.29 x 28.70
Shipping Weight (lbs.)	46.10
Shipping Weight (kg)	20.91
UPS Housing Material	PVC
UPS Power Module Dimensions (hwd, cm)	32.51 x 19.05 x 23.37
UPS Power Module Dimensions (hwd, in.)	12.8 x 7.5 x 9.2
UPS Power Module Weight (kg)	16.51
UPS Power Module Weight (lbs.)	36.4
Unit Dimensions (hwd / in.)	12.750 x 7.500 x 9.250
Unit Weight (Ibs.)	36.4000
Unit Weight (kg)	16.51
ENVIRONMENTAL	
Operating Temperature Range	32° to 104°F (0° to 40°C)
Storage Temperature Range	5° to 122°F (-15° to 50°C)
Relative Humidity	0 to 95%, non-condensing
AC Mode Efficiency Rating (100% Load)	91%
AC Economy Mode Efficiency Rating (100% Load)	0.91
Operating Elevation	0-6562 ft. (0-2000 m)
COMMUNICATIONS	
PowerAlert Software	For local monitoring via the UPS's built-in USB port, download PowerAlert software at https://tripplite.eaton.com/products/power-alert
Communications Cable	USB cable included
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
Insertion Loss	65 db N-G from 10Khz to 100Khz, 45 to 60 db L-G from 10Khz to 100Khz, 18 to 54 db L-N from 50Khz to 500 Khz
Network Management Card Description	Network management not supported





Communications Interface	USB		
LINE / BATTERY TRANSFER			
Transfer Time	6 milliseconds typical (10 milliseconds max)		
Low Voltage Transfer to Battery Power (Setpoint)	81		
High Voltage Transfer to Battery Power (Setpoint)	143		
FEATURES & SPECIFICATIONS			
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported		
High Availability UPS Features	Hot swappable batteries; Surge/noise protection		
APPLICATIONS			
UPS Applications	High-End Desktop/Small Network; Retail/Point of Sale; Hospitality		
STANDARDS & COMPLIANCE			
Product Certifications	CSA (Canada); NOM (Mexico); UL 1778		
Product Compliance	RoHS; FCC Part 15 Class A (USA)		
WARRANTY & SUPPORT			
Product Warranty Period (Worldwide)	2-year limited warranty		
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$200,000 <a class="insuranceLink" href="//tripplite.eaton.com/support/insurance-policy">Ultimate Lifetime Insurance</a>		

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.