

# 240V Corded UPS Backplate Outlet Kit for SU6000RT3, L6-30R, L6-20R, 5-15/20R

**MODEL NUMBER: SUPDM13** 



#### **Highlights**

- Converts Tripp Lite's hardwire SU6000RT3U UPS systems to one with AC plug and outlets
- For use with 240V UPS output voltage configurations
- 10 ft. / 3m AC input power cable with NEMA L6-30P input plug
- 1 L6-30R, 2 L6-20R and 10 5-15/20R output receptacles
- Easy quick-connect wiring installs in minutes

#### **Description**

Tripp Lite's SUPDM13 corded backplate kit converts Tripp Lite's hardwire SU6000RT3U UPS system into one with AC plug and outlets. 10 ft./3m input line cord with L6-30P plug enables simple connection to 240V 30A mains power. Includes 1 L6-30R, 2 L6-20R and 10 5-15/20R output receptacles. Easy quick-connect wiring installs in minutes.

VOLTAGE COMPATIBILITY NOTE - SUPDM13 supports SU6000RT3U applications configured for 240V nominal input voltage only (See SUPDM12 for 208V input voltage configurations).

### **Features**

- Converts Tripp Lite's hardwire SU6000RT3U UPS system to one with an AC plug and outlets
- 10 ft./3m AC line cord with L6-30P input plug-in connection
- Includes 1 L6-30R, 2 L6-20R and 10 5-15/20R output receptacles
- Easy quick-connect wiring installs in minutes

## **Specifications**

OVERVIEW	
UPC Code	037332120847
Accessory Type	Backplate Outlet Kit
Accessory Class	UPS Accessories
INPUT	
Nominal Input Voltage(s) Supported	208V AC
UPS Input Cord Length (ft.)	10



3.1	
30A 240V	
NEMA L6-30P input plug	
208	
OUTPUT	
(10) 5-15/20R; (2) L6-20R; (1) L6-30R	
Simultaneous 240 and 120V output	
120V outlets are protected by 2 separate 20A branch rated circuit breakers	
PHYSICAL	
Steel	
5.00 x 13.50 x 9.10	
12.70 x 34.29 x 23.11	
5.60	
2.54	
3.500 x 5.000 x 11.000	
6.4 x 12.7 x 28	
6	
2.72	
WARRANTY & SUPPORT	
2-year limited warranty	

1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.